

**MODELS LI118B / LI123B**

ARCHITECTS' AND ENGINEERS' SPECIFICATIONS

The corridor dome lights with built-in buzzers shall be Alpha Communications®/Tektone LI118B (24VDC) or LI123B (24VAC) or approved equal. Lights shall include a translucent plastic cover mounted on a flame retardant ABS plastic panel, which shall be removable for bulb replacement, without the use of any tools. Units shall mount over a conventional 2-gang electrical back box.

Built-in buzzers shall sound as long as the dome light is lighted (activated).

Contractor shall observe all local and national electrical and building codes.

LI118B/LI123B Corridor Lamps With Built-in Buzzers

The Alpha Communications® LI118B (24VDC) and LI123B (24VAC) Corridor Lamps provide both visual and audible indications of any type of call. Models may be used with an emergency call system or in any application where this type of audible and visual call indication is needed.

The standard mounting plate accommodates both models and features an easily removable white translucent cover for bulb replacement.

FEATURES

- Excellent Visibility
- Audio call indication
- Easy Bulb Replacement - No Tools Required
- Durable construction

SPECIFICATIONS

<u>Dimensions:</u>	Height: 4.56" (116mm) Width: 4.56" (116mm) Projects: 3.00" (76mm) from mounting surface
<u>Bulb:</u>	Type 1829, 28V, min. Bayonet Mt.
<u>AC Buzzer:</u>	Type 123A-G5, 24 VAC, 160mA
<u>DC Buzzer:</u>	Type 118-G1, 24 VDC, 40mA
<u>Power:</u>	LI118B: 24VDC, 91mA LI123B: 24VAC, 211mA
<u>Mounting:</u>	Fits standard 2-gang box. Minimum depth of box to be no less than 1.75".
<u>Finish:</u>	Translucent white plastic cover mounted on a flame retardant, fog white ABS plastic panel.

OPTIONAL EQUIPMENT

AEC100	Master Annunciator (or other type)
SS106	Transformer
PK601A	DC power supply
SF117/2A	Pull cord switch (or equivalent)
SF154A	Push type switch (or equivalent)

Due to continuous product improvement, all colors, sizes, materials, finishes and specifications are subject to change without notice.