



WF32/S

ARCHITECTS' AND ENGINEERS' SPECIFICATIONS

The apartment intercom station(s) shall be Alpha®/S.T.R.™ WF32/S. Station(s) shall be surface mounted. Station(s) shall feature amplified simplex voice communication. Stations that include carbon transmitter or other voice technologies shall not be acceptable. Station(s) shall have a textured finish to minimize scratches. Station(s) shall include a Door release (KEY SYMBOL) button and Talk/Listen (SPEAKER) push button. Station(s) shall include an adjustable volume AC buzzer for signalling from the lobby entry panel. Station(s) shall also allow a tone signal to sound upon activation of any individual (optional) apartment door buttons. Station(s) shall mount directly to the finished wall surface or over a single gang electrical (gem) box or plaster ring. Contractor shall observe all local and national electrical codes.

Copyright© 1998-2000, Alpha Communications®, All Rights Reserved

WF32/S Wall Mount Apt. Intercom Station

The Alpha®/S.T.R.™ WF32/S apartment intercom stations are designed with a single (oversized) Talk/Listen button to simplify operation, and to eliminate switching back and forth between separate Talk and Listen buttons. When called, the tenant simply presses the button to Talk and releases to Listen. The Listen mode will time-out automatically in approximately 20 seconds, or immediately upon activation of the Door release push-button.

These attractive stations easily surface mount right onto the finished wall or over a single gang flush electrical (gem) box (or plaster ring). Stations can be changed to desk mount with the addition of a model TZWFWH desk adaptor.

All WF32/S stations feature textured finish (to minimize scratches and fingerprints), electric buzzer signalling (adjustable), electronic tone signaling for individual apt. door call buttons and (2) two momentary button switches. The button with the speaker symbol is used for Talk/Listen operation and the button with the key symbol is used for electric door release.

FEATURES

- Convenient One-Button Simplex Voice Operation
- Easy Installation
- Communication Privacy
- Oversized Push-buttons (for Children and Senior Citizens)
- Rugged and Reliable
- Simple to Operate-No Switching Between Talk and Listen Buttons
- Convenient 5-Wire Installation (4-Common/1-Selective) (add 1-Common wire for individual apartment door tone signals).
- Attractive Styling Blends with Any Decor

SPECIFICATIONS

Dimensions: All WF32/S apt. stations are 3.38"W (86mm) x 5.75"H (147mm) x 1.25"D (32mm).

Speaker: 70mm round, 16 ohms, Model L4.

Finish: White ABS Plastic with Textured Finish

Push Buttons: (1) with Door Opener (KEY) symbol and (1) with Talk/Listen (SPEAKER) symbol.

Amplifier: Model TV32/S (1 required per system).

Options: Model TU5/S Dual Entrance Adaptor.

Due to continuous product improvement, all colors, sizes, materials, finishes and specifications are subject to change without notice.