



**IR088A**

## ARCHITECTS' AND ENGINEERS' SPECIFICATIONS

Suite station(s) shall be Alpha Communications®/Tek-tone IR088A, or approved equal and shall be large enough to cover the area occupied by the previous Auth 777 series (or equivalent) intercom unit. Momentary action push buttons shall be provided for TALK, LISTEN, and DOOR operations. The speaker/microphone shall be a 3.50" high-sensitivity type with voice-frequency response. Positive screw terminal connections shall be provided and required wiring shall be only three (3) common and one (1) selective wires.

Unit(s) are supplied without mounting screws, or mounting holes, unless custom ordered, at additional cost.

Contractor shall observe all local and national electrical and building codes.

Copyright© 1999-2009, Alpha Communications®, All Rights Reserved

## IR088A Oversized Apartment Intercom Stations

The Alpha Communications® IR088A apartment stations are designed specifically for renovation use and are large enough to cover the area occupied by the existing intercom units, making repainting unnecessary. The reduced wiring requirement permits using the existing wiring (if in good condition), while the advanced electronic design permits use in large or small buildings. A wide variety of optional accessories is available to provide additional functions such as dual entrance operation, post office door release, silent door operation, etc. Stations are also available in custom designs.

### FEATURES

- Simple push button operation
- Automatic Privacy
- Easy Installation
- Elongated panel faceplate covers Auth 777 or equivalent intercom station flush housings
- Attractive Steel Faceplate with White Vinyl Coat Finish

### SPECIFICATIONS

**Dimensions:** Height: 12.50" (318mm)  
Width: 5.50" (140mm)

**Construction:** Steel faceplate with white vinyl coat

**Controls:** Individually replaceable push buttons with self wiping contacts. Identified for TALK, LISTEN, and DOOR functions.

**Speaker/Mic:** 3.50" (89 mm) with voice response. Also used for electrical tone signal.

**Mounting:** Mounting holes are pre-punched to accommodate existing Auth 777 flush back-box. Supplied without mounting screws unless custom ordered.

### SYSTEM OPERATION

The caller, by pressing the appropriate button on the entrance panel, causes an electronic call tone to be sounded in the apartment station being called. The resident may then determine the identity of the caller and permit entry to the building, if so desired, by operating the apartment station as follows:

<b>TALK</b> button	Push while speaking to caller
<b>LISTEN</b> button	Push while listening for reply
<b>DOOR</b> button	Push to allow entry to building

*Do to continuous product improvement, all colors, sizes, materials, finishes and specifications are subject to change without notice.*