



**E-144**  
(shown without cord and pendant)

### ARCHITECTS' AND ENGINEERS' SPECIFICATIONS

The Emergency Pull station(s) shall be Alpha Communications®/Cornell E-144, or approved equal with momentary pull cord operated switch, mounted on a durable Stainless Steel faceplate marked "EMERGENCY", permanently silk-screened onto the faceplate.

Unit shall mount on single-gang electric "gem" box or plaster ring. Unit shall feature a 'Momentary' switch that activates when the six (6) foot nylon cord is pulled. Unit shall have pigtail wire connectors.

The Emergency Call switch may be used with 'stand-alone' emergency systems, or the CM800 series annunciator(s).

Contractor shall observe all local and national electrical and building codes.

### E-144 Emergency Pull Station

The Alpha Communications® E-144 Emergency Pull station is used to initiate a system 'Emergency' signal. It may be used independently or connected with other call stations and/or intercom stations. The E-144 has a spring loaded switch that activates in a 'Momentary' fashion, only as long as the pull cord is pulled.

Placing a call is accomplished by pulling on the pull cord. This type of 'Momentary' is usually canceled except at the master annunciator station(s). The E-144 station features a rugged stainless steel faceplate, with the word 'EMERGENCY' permanently silk-screened onto the faceplate.

#### FEATURES

- 'Momentary' Pull Cord Activation
- Built-in Pull Cord and Pendant
- Rugged Stainless Steel Faceplate

#### SPECIFICATIONS

**Dimensions:** Height: 4.50" (114mm)  
Width: 2.75" (69mm)  
Depth: 1.75" (45mm) into wall  
Projects: 0.50" (13mm) from mounting surface

**Connections:** Pigtail Connections

**Mounting:** Steel City #52171 box with Steel City #52C14 plaster ring, or Alpha Communications® Model #IH358 box with IH357 ring, or EXACTEQUAL. Vertical mount.

*Due to continuous product improvement, all colors, sizes, materials, finishes and specifications are subject to change without notice.*