



# Product Specification Sheet



APS497

Rev. 3 - 02/2009



SF382 (shown without optional CA015K pull cord assembly)

## ARCHITECTS' AND ENGINEERS' SPECIFICATIONS

Addressable Code Call station(s) shall be Alpha Communications®/TekTone SF382 or approved equal. Code stations and wiring shall be fully supervised. Operation of emergency signals shall be accomplished by a short pull on the (optional) nylon cord or by pulling/pushing down on the BLUE lever marked "CODE". The RED "CALL-PLACED" indicator shall flash to assure that the call has been properly placed. The initiation of the code call shall cause the activation of both audible and visual signals. Call cancellation shall be possible only at point of origination. Reliable, solid-state components shall be used and plug-in connectors shall be provided for electrical connections.

Contractor shall observe all local and national electrical and building codes.

Copyright© 2002-2009, Alpha Communications®, All Rights Reserved

## SF382 Addressable Code Call Station

The Alpha Communications® SF382 may be used in ICU/CCU, physical therapy rooms, post-op recovery, or any location where code call initiation may be required., without the need to install another device (such as a multipurpose station or other addressable device). The SF382 is designed to be connected directly to the station buss wiring of either the NC300 or the NC300II system. The SF382 includes dome lamp output, and is addressed using dip switches mounted on the rear of the SF382.

Due to the flexibility of its design, it may be used as a PULL CORD CODE STATION, or a PUSH TYPE CODE CALL STATION. The optional (model CA015K) pull cord may be used for emergency pull activation, or if so desired, the standard LARGE BLUE push/pull down lever may be used.

The SF382 is typically used with the NC300 and/or NC300II or HC345 systems. The SF382 is not designed for use in a shower or 'moist' environment.

## FEATURES

- Fully supervised
- Simple and flexible operation
- Registers audible and visual calls at master station
- Indicates local call origination on dome lights
- Call cancellation only at point of origin
- Flame retardant type KJB Cycolac Plastic
- 1.5" wide BLUE Pull-Down lever
- Can be used as a PUSH type station or PULL type (using optional model CA015K pull cord assembly)

## SPECIFICATIONS

<b>Dimensions:</b>	Height: 4.50" (114mm) Width: 2.81" (72mm) Depth: 1.63" (41mm) Projects: 0.69" (17mm) from mounting surface (including pull down lever)
<b>Construction:</b>	Electronic components and DPDT switch, circuit board mounted
<b>Connections:</b>	Plug-in connector
<b>Housing:</b>	Steel City #52171 box with Steel City #52C14 plaster ring, or Alpha Communications® Model #IH358 box with IH357 ring, or EXACT EQUAL. Vertical mount.

*Due to continuous product improvement, all colors, sizes, materials, finishes and specifications are subject to change without notice.*