



CSM-44-Camera Switching Module



Installs
Here



ARCHITECTS' AND ENGINEERS' SPECIFICATIONS

The 4-camera switching module(s) shall be Alpha Communications®/S.T.R.™ CSM-4. Switching module(s) shall be installed in place of the blank module(s) found between the monitors and the handsets. Switching module(s) shall feature four (4) front mounted momentary push buttons marked CAM1, CAM2, CAM3 and CAM4. Switching module(s) shall be finished in the same white plastic finish as the monitor handsets and button markings shall be silk-screened.

Contractor shall furnish and install the necessary TU1007A and DPS-2 switching components, as required, and any compatible CCTV cameras needed.

Contractor shall observe all local and national electrical codes.

CSM-44-Camera Switching Module

The Alpha Communications®/S.T.R.™ CSM-44 Camera Switching Modules are designed to be used with the VH30 series video-intercom monitor stations. The CSM-4 installs in place of the blank panel found between the monitor and the handset, allowing the resident to switch between up to four (4) CCTV cameras at various building locations.

The four (4) camera switching buttons are marked CAM1, CAM2, CAM3 and CAM4 and match the styling found on the monitor handsets. The CSM-4 is easily installed in place of the blank module and can be added to the monitor(s) at a later time if required.

FEATURES

- Four (4) Momentary Buttons marked CAM1, CAM2, CAM3 and CAM4
- Easily installs in place of blank module
- Matches styling of handset buttons
- Rugged and Reliable. Simple to Operate

SPECIFICATIONS

Dimensions: 1.10"W (28mm) x 8.50"H (216mm) x 0.75"D (20mm).

Finish: Same White Plastic as found on the HT3003/2WH monitor handset

Markings: Silk-Screened

NOTES: For switching to 1-2 cameras you must add 1- TU1007A and 1- DPS-2 switching units to the main system power supply. For switching to 3-4 cameras you must add 2- TU1007A and 2- DPS-2 switching units to the main system power supply. The blank buttons shown on the top are used for other purposes and do not function on the CSM-4 units.

Due to continuous product improvement, all colors, sizes, materials, finishes and specifications are subject to change without notice.