



**SF154AM**

### **ARCHITECTS' AND ENGINEERS' SPECIFICATIONS**

Momentary Emergency Push Station(s) shall be Alpha Communications® SF154AM or approved equal.

Operation of all system emergency signals shall be accomplished by depressing the push button switch. When activated, the momentary switch shall provide a Normally Open or Normally Closed dry contact closure. The switch shall be mounted on a white plastic faceplate, marked 'EMERGENCY' in black lettering. Faceplate shall be made of flame retardant White ABS plastic. Standard mounting screws shall be provided.

Contractor shall observe all local and national electrical and building codes.

### **SF154AM Momentary Emergency Push Call Station**

The Alpha Communications® SF154AM momentary push type emergency station is used to initiate system emergency signals. Signaling an emergency is accomplished by depressing the momentary push button switch located at the center of the faceplate. Once depressed, a Normally Open or Normally Closed type dry contact closure will be activated for as long as the button is depressed. The call signal would typically be cancellable at a remote location.

#### **FEATURES**

- Simple, reliable momentary operation
- Call activates lamp on annunciator panel and corridor lamp.
- Mounted on attractive flame retardant white ABS plastic faceplate with the word EMERGENCY in black lettering

#### **SPECIFICATIONS**

- Dimensions:** Height: 4.50" (114mm)  
Width: 2.75" (70mm)  
Depth: 2.44" (52mm)
- Panel:** Flame retardant White ABS plastic faceplate
- Connection:** Wire pigtail leads
- Mounting:** Steel City #52171 box with Steel City #52C14 plaster ring, or Alpha Communications® Model #IH358 box with IH357 ring, or EXACTEQUAL. Vertical mount.
- Marking:** Marked EMERGENCY in Black lettering

*Due to continuous product improvement, all colors, sizes, materials, finishes and specifications are subject to change without notice.*