



PK724 AMPLIFIER

**ARCHITECTS' AND ENGINEERS'
SPECIFICATIONS**

The system power supply/amplifier(s) shall be Alpha Communications®/Tektone model PK724, or approved equal. Unit(s) shall provide the audio, electronic chime and power circuits needed to power the entire intercom system. Unit(s) shall also provide an input for a background music source or separate electronic chime, or other compatible audio source. Low voltage wiring shall be used and a plug-in wiring harness shall be provided for installation wiring. Unit(s) shall have separate intercom and electronic chime volume controls, and shall have a 2-note and 1-note electronic chime built-in.

Contractor shall observe all local and national electrical and building codes.

Copyright© 1999-2005, Alpha Communications®, All Rights Reserved

**PK724 System Amplifier
With Electronic Chime**

The Alpha Communications® PK724 power supply/amplifiers are used with our IR704B, IR704BVC, IR704BD and IR804A series intercom stations. They provide audio intercom, electronic chime and system power for the entire system.

The PK724 easily mounts right on the surface of the wall and a plug-in wiring harness makes installation quick and easy.

Each system requires only one (1) PK724 power supply/amplifier.

FEATURES

- Has (2) built-in Electronic Chime Sounds
- Operates on Safe Low-Voltage Class II Wiring
- Convenient Plug-In Wiring Harness
- OPTIONAL music or audio input

SPECIFICATIONS

Dimensions: Height: 5.50" (140mm)
Width: 3.125" (83mm)
Depth: 2.00" (51mm)

Construction: Rugged ABS White Plastic Casing.

Connections: Polarized plug in type wiring harness

Mounting: Surface mount.

Power Required: 16VAC using the **SS102A** (pigtail) or **SS105B** (plug-in) type system transformer.

Due to continuous product improvement, all colors, sizes, materials, finishes and specifications are subject to change without notice.