



**Ovation 'No Phone Line'  
Central Equipment**



**OV-LIB3  
12-Line Relay Board**  
(for use with the 'Ovation'  
Lobby Entry Master Station  
or with DPW100W Concierge Phone)

**ARCHITECTS' AND ENGINEERS'  
SPECIFICATIONS**

Relay board(s) shall be Alpha Communications®/ Sentex model OV-LIB3 and shall be compatible with the OV-VPLP-SS (or equivalent) 'Ovation' lobby entry master station and/or DPW100W series lobby/concierge/guard stations and OV-LP central control unit.

For 'no phone line' service capability system shall include the following components; OV-LIBH-3 Relay Board Cabinet (for each 36 lines/telephones), OV-LIBH-10 Relay Board Cabinet (for each 120 lines/telephones), OV-LIB3 Relay Board (1 per 12 lines/telephones), and a 15CABLE Connector Cable Assembly (1 per OV-LIB3). All equipment should be located in the telephone room. Local phone company shall provide and install the required RJ71C (12 line) interface jack(s) required (1 per OV-LIB3).

Contractor shall observe all local and national electrical and building codes and F.C.C. regulations

**OV-LIB3 12-Line  
Relay Board**

The Alpha Communications® OV-LIB3 12-Line Relay Board is designed to provide 'no phone line capability' when interfaced with the Alpha Communications® OV-VPLP-SS lobby entry master station or DPW100W (concierge/guard) master/phone stations, and OV-LP control cabinet.

One (1) OV-LIB3 is used for each 12 (or fewer) remote telephones that need to be connected to the telephone entry system. Each OV-LIB3 requires a model 15CABLE connecting cable and a customer supplied RJ71C phone jack (usually installed by the local phone co.).

**FEATURES**

- Provides 'No Phone Bill' (aka 'No Phone Line') capabilities for up to 12 remote telephones (each)
- Simple plug-in connections to OV-LIBH-3 or OV-LIBH-10 housing(s)

**SPECIFICATIONS**

<b>Dimensions:</b>	OV-LIBH-3	7.00"W (178mm) x 13.25"H (337mm) x 6.25"D (159mm)
	OV-LIBH-10	17.25"W (439mm) x 13.25"H (337mm) x 6.25"D (159mm)

**REQUIRED COMPONENTS**

<b>OV-VPLP-SS</b>	Steel Series Telephone Entry Master Station (or other model 'Ovation' master)
<b>OR</b>	
<b>DPW100W</b>	Concierge/Guard Telephone Station
<b>OV-LIBH-3</b>	Relay Board Cabinet (holds up to 3 OV-LIB3 boards)
<b>OV-LIBH-10</b>	Relay Board Cabinet (holds up to 10 OV-LIB3 boards)
<b>OV-LP</b>	Control Unit (2700 lines)
<b>OV-LIB3</b>	Relay Board (1 per 12 lines/telephones)
<b>15CABLE</b>	Connector Cable Assembly (1 per OV-LIB3)

*Due to continuous product improvement, all colors, sizes, materials, finishes and specifications are subject to change without notice.*