



**HT3000 Series Handsets  
White Shown with optional  
TZ1003 Desk Adaptor  
Anthracite Shown with optional  
UM3004 Flush Adaptor  
and Trim Ring**

### ARCHITECTS' AND ENGINEERS' SPECIFICATIONS

The handset station shall be Alpha Communications®/S.T.R.™ HT3009/2 (2-Wire) or HT3003/2 (5-Wire), in (White, Titanium or Anthracite) color. Handset shall be mounted (surface, flush or desktop). Handset shall feature electret condenser microphone for exceptional voice fidelity. Handsets that include carbon transmitter or other voice technologies shall not be acceptable. Handset shall have a textured finish and high-quality coil cord. Handset shall include a door release (KEY SYMBOL) button and auxiliary (DOT) push button. Push buttons shall be clearly visible and shall be marked in a different color. Handset shall include a built-in AC buzzer (or optional R2007 Alphonet™ adaptor). Contractor shall observe all local and national electrical and building codes.

Copyright© 2001-2009, Alpha Communications®, All Rights Reserved

### HT3000 Series Handsets

The Alpha®/S.T.R.™ HT3000 Series handsets are designed to work as an apartment type handset intercom station or for industrial and commercial building entry applications.

Choose from White or Anthracite (Charcoal) in either a 2-Wire (HT3009/2) or 5-Wire (HT3003/2) configuration, depending upon the system in which it is being used.

These attractive handsets easily surface mount right on the wall or over a single gang flush electrical back box (or plaster ring). Handsets can be changed to desk mount with the addition of a model TZ1003 desk adaptor, or can be flush mounted with the addition of a Model UM3004 flush housing/trim assembly.

All HT3000 series handsets feature textured finish (to minimize scratches and fingerprints), electric buzzer signalling, high quality (replaceable) coiled cord and (2) two momentary button switches. These switches can be used for door release, paging or other signalling functions, depending upon system configuration.

With the addition of a low-cost Model R2007 Alphonet™ chime adaptor, you can easily change the electric buzzer to a modern warble chime tone sound.

### FEATURES

- Convenient Half-Duplex Voice Operation
- Easy Installation
- Eavesdrop Privacy
- Clear Voice Fidelity using Electret Condenser Microphones
- Rugged and Reliable / Simple to Operate
- Mounts Flush, Surface or Desk
- Available in White, Titanium or Anthracite (Charcoal) color

### SPECIFICATIONS

**Dimensions:** All HT3000 series handsets are 3.75"W (96mm) x 8.75"H (223mm) x 2.60"D (67mm). All dimensions shown are for the surface wall type handset, less the coiled cord.

**Receiver:** 50mm round, 45 ohms, Model HK1.

**Microphone:** Electret Condenser Type

**Push Buttons:** (1) with Door Opener (KEY) symbol and (1) spare (Dot).

*Due to continuous product improvement, all colors, sizes, materials, finishes and specifications are subject to change without notice.*